

VAIA Wall-mounted single-lever basin mixer without pop-up waste - Brushed Champagne (22kt Gold)

VAIA

36 860 809



- 190mm projection
- fixed spout
- circular, air-enriched flow
- hole diameter spout 37 mm
- hole diameter single-lever mixer 57 mm
- rosette for single-lever mixer Ø 78mm
- rosette for spout Ø 60mm
- max. flow 4.5 l/min
- lead-free
- This product can help a building meet the requirements of Green Building Rating Systems, e.g. LEED®, BREEAM®, DGNB

	Brushed Champagne (22kt Gold)	36 860 809-46 0010
	Chrome	36 860 809-00 0010
	Brushed Platinum	36 860 809-06 0010
	Platinum	36 860 809-08 0010
	Dark Chrome	36 860 809-19 0010
	Brushed Durabronze (23kt Gold)	36 860 809-28 0010
	Brushed Bronze	36 860 809-42 0010
	Champagne (22kt Gold)	36 860 809-47 0010
	Brushed Dark Platinum	36 860 809-99 0010

Required miscellaneous




Concealed wall-mounted single-lever mixer - 35 860 970-90 0010

- max. recess depth 95 mm
- min. recess depth 80 mm
- Rough can be rotated to position the lever on top or to the left of the spout.

VAIA Wall-mounted single-lever basin mixer without pop-up waste - Brushed Champagne (22kt Gold)

VAIA

36 860 809
mm [inches]



Codes & Standards

ADA	ASME A112.18.1	California Energy Commission (CEC)	cUPC
NSF372	NSF61		


Certificates and sustainability

IAPMO_N-4976 IAPMO_6397 IAPMO_4976 (

VAIA Wall-mounted single-lever basin mixer without pop-up waste - Brushed Champagne (22kt Gold)

VAIA

36 860 809



Spare parts list

No.	Item Number	Name	Quantity used	Delivery time
7	90 27 80 012 00-46	rosette	1.00	30
1	09 24 03 072 10 90	nipple	1.00	2
6	09 11 02 288-46	cover	1.00	60
5	90 31 20 087 00-46	plug	1.00	30
2	13 800 809-46 0010	VAIA Wall-mounted basin spout without pop-up waste - Brushed Champagne (22kt Gold)	1.00	-
Spare part can no longer be ordered, please order the replacement item				
3	09 20 80 021-46	handle	1.00	30
8	90 15 05 064 01 90	cartridge	1.00	2
9	90 30 09 064 00 90	key	1.00	2
4	90 31 11 063 00 90	pin	1.00	2
10	12 869 970 90	Extension 20 mm -	1.00	2